



# TJS-BA1002WAP

## TJS-BA1002WAP

### General Features:

- LCD Colour Screen
- Touchpad
- Tamper Alarm
- Up to 20 RFID Cards
- Up to 20 Smart Sockets
- Up to 99 Wireless Detectors
- Remote Control App

### Dimensions:

176 x 135 x 17 mm

### Colour:

- Black
- White



Model:	TJS-BA1002WAP
LCD Screen	Segment LCD screen with touchpad
Languages	English (Spoken)
Power Supply AC	220V ± 10%
Working Voltage	9 - 12VDC
Power Consumption	Standby: < 25 mA Alarm: < 450 mA
Build-in Battery	NI-HI Battery 1.5V
Battery Stand-by Time	6 - 10 Hrs
Tamper Alarm	YES
Communication Method	GSM
GSM / GPRS Band	850 / 900 / 1800 / 1900 MHz
Radio Frequency	315 / 433 MHz
Alarm Protocol	Contact ID
Alarm Volume	< 120 dB
Alarm Schedules	4 Different Schedules
Alarm Zones	99 Zones
Zone Types	Normal Zone Stay Zone Intelligent Zone Emergency Zone Closed Zone Chime Zone Welcome Zone Help Senior Zone
Zone Siren	Siren can be ON / OFF in each zone separately
Alert Calling	Up to 8 Phone Numbers numbers 1 - 6 are telephone function numbers 7 - 8 are CID
ISD Auto-Record	10 Seconds
Remote Control App	Arming / Disarming Monitoring Speaking Siren ON / OFF Relay ON / OFF Control Smart Sockets
Relay Output	1 NO Relay Signal Output
Wired Detectors	max. 2 Detectors
Wireless Detectors	max. 99 Detectors
7 Event Codes For Each Detector	Mecical Fire Robbery Silent Robbery Burglar Perimeter Gas
Remote Controls	max. 99 Remote Controls
RFID Cards	max. 20 RFID Cards All Cards have unique number
Smart Sockets	max. 20 Smart Sockets
Wireless Distance	< 150 mtrs
Dimensions	176 x 135 x 17 mm
Working Temp.	-10 ~ 40°C
Working Humidity	< 80%